

# STUDIO PAR 64 CAN TRI 3W

## DMX CONTROL TABLE



CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0-100 %)
CH2	000 - 255	RED (0-100%)
CH3	000 - 255	GREEN (0-100%)
CH4	000 - 255	BLUE (0-100%)
CH5	000 - 004 005 - 084 085 - 169 170 - 255	No function Colour macro Colour ( speed ) Colour fade
CH6	000 - 255	Strobe ( speed )